

LOW - VOLTAGE PENDANTS

Kiev Pendant LED SORAA T20

DESCRIPTION

Antique meets modern with a turned ornate glass fount and simple tapered fabric shade with rolled edges. Includes low-voltage, 50 watt halogen bi-pin lamp or 8 watt, 300 delivered lumen, 3000K, replaceable SORAA® LED module and six feet of field-cutttable cable. Dimmable with low-voltage electronic or magnetic dimmer (based on transformer). Works with SORAA.

INSTALLATION

Socket terminates with FreeJack male connector, which may be installed into a system connector. Elements ordered with a system prefix include a connector for that system. For use on T~TRAK, order FreeJack version and T~TRAK FreeJack Connector (sold separately).

ACCESSORIES & OPTICAL CONTROLS

SORAA® LED Bi-Pin Replacement Pendant Module, Swag Hook

WEIGHT

0.91lb / 0.41kg ±



black shade



black
smoke fount



white
clear fount



white
frost fount

ORDERING INFORMATION

| 700 | SYSTEM | KIE | COLOR | Fount Color | FINISH | LAMP |
|-----|----------------------|-----|---------------|---------------|------------------|---|
| FJ | FREEJACK | | B BLACK SHADE | C CLEAR FOUNT | Z ANTIQUE BRONZE | 12 VOLT HALOGEN (T20) |
| KL | KABLE LITE | | W WHITE SHADE | F FROST FOUNT | C CHROME | -LEDS930 12 VOLT LED 90 CRI 3000K (T20/T24) |
| MP | MONOPOINT | | | K SMOKE FOUNT | S SATIN NICKEL | -24 24 VOLT HALOGEN |
| MO | MONORAIL | | | | | |
| MO2 | TWO-CIRCUIT MONORAIL | | | | | |

Note: Note: MP includes 4" Round Flush Canopy.

Antique Bronze is not available for Kable Lite.

Chrome not offered on Monorail & Two~Circuit Monorail.



700 ____ KIE _____

FIXTURE TYPE: _____

JOB NAME: _____

NOTES: _____
